


### Safety notes:

Installation must be performed only by a qualified electrician.

Make sure that the fixture is disconnected from the AC supply.

This luminaire is to be installed in 3-wires/1-phases or 4-wires/3-phases or 6-wires/3-phases DALI track rails.




### Features:

Perfect solution for the retail business, shops, and supermarkets.

Excellent quality with high efficiency up to 160lm/W.

Four selectable powers with DIP switch.

Flexible position of the luminaire in the rail by sliding left or right.




European standard

- 1 Ground point
- 2 Adaptor knob
- 3 Phase selector
- 4 Ground pin
- 5 Power selector
- 6 LED driver
- 7 Wires lock
- 8 Wires box
- 9 Fixing lock
- 10 Fixing knob
- 11 End cap
- 12 Track rail
- 13 Suspension kit


#### Step 1

Set the power in the **5 power selector** DIP switch.




#### Step 2

Choose the phase/circuit in the **3 phase selector** DIP switch.




#### Step 3

Insert the T-line luminaire into the **12 track rail** with the correct direction.



#### Step 4

Lock the luminaire with the **2 adaptor knob** and the **10 fixing knob** by rotating the knobs clockwise.




### How to avoid the track rail joints during installation

There are 4 movable positions for the LED driver in the T-line luminaire.  
There are 2 movable position of the fixing lock in the T-line luminaire.




If the **12 track rail** joint interferes with the position of the **9 Fixing lock**, follow the instruction of **Step 1**.


If the **12 track rail** joint interferes with the position of the **6 LED driver**, follow the instructions from **Step 2** to **Step 5**.




**Step 1**  
Slide the **9 fixing lock** left or right to the second position to avoid the **12 track rail** joint.




**Step 2**  
Expose the wires in the **8 wires box** by moving it to the right.



**Step 3**  
Slide the **6 LED driver** left or right to a free position.




**Step 4**  
Slide the **8 wires box** near the **6 LED driver**.  
Tidy up the wires and hide them by sliding the **8 wires box** back.



**Step 5**  
Install the T-Line luminaire into the **12 track rail**.


### Luminaire installation guidance




**Step 1**  
Install luminaire into the track rail



**Step 2**  
Rotate the left side of the luminaire alone




**Step 3**  
Rotate the right side of the luminaire alone



**Step 4**  
Rotate both left and right sides of the luminaire

### Track rail

- 3-wires/1-phases
- 4-wires/3-phases
- 6-wires/3-phases



### Recommend track rail brands

Pay attention to the positioning knob. No Reverse Mount!  
Improper installation may cause irreparable damage.

